

# POWER METER DUAL

Remotely monitor power consumption of two electric loads with this compact Z-Wave module. You can easily hide it in a electricity box without altering decoration of your premises. Save energy and money with Zipato Power Meter Dual.



## DESCRIPTION

Zipato Power Meter Dual monitors total electricity consumption of connected appliances and reports it to Zipato or any other Z-Wave enabled controller in real time. Small and compact size allows easy installation in majority of electricity distribution boxes. It supports two loads up to 6000W each (@ 120V).

## PRODUCT FEATURES

- Slim, compact remote Z-Wave module measures power parameters of connected device
- Dual power meter function
- 2 amper meter clamps are included in the box
- Instant power wattage and Accumulated power consumption KWh report
- Maximum current measure 60A
- New Z-Wave 500 series
- Very low power consumption
- Over-the-air firmware update
- Easy installation

## TECHNICAL SPECIFICATION

### PROTOCOL

- Z-Wave Plus

### OPERATING VOLTAGE

- 100~240VAC

### MAXIMUM LOAD

- 6000W X 2 @ 120V

### OPERATING TEMPERATURE

- 0°C ~ 40°C

### OPERATING HUMIDITY

- 10% TO 85%RH

### STORAGE TEMPERATURE RANGE

- -20°C ~ 60°C

### FREQUENCY

- ph-pab01.au 921.42 MHz (AU)
- ph-pab01.eu 868.42 MHz (EU)
- ph-pab01.in 865.20 MHz (IN)
- ph-pab01.is 916.02 MHz (IS)
- ph-pab01.ru 869.02 MHz (RU)
- ph-pab01.us 908.42 MHz (USA/Canada)

### DIMENSIONS

- -
- -
- -

### WEIGHT

- -
- -
- -

### REGULATION

- EMC 2004/108/EC, R&TTE 1995/5/EC, LVD 2006/95/EC, FCC Part 15

### WARRANTY

- 1 year standard

NOTE: SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT PRIOR NOTICE